



Desktop / Portable AC/DC Digital PLL Radio BTD-7000 (Black) / BTD-7001 (White)

Sales start
August 2011

Order number
9 000 007 000 (black)
9 000 007 001 (white)

EAN number
7640150855148 (black)
7640150855155 (white)

Highlights

- Band: FM (RDS), MW, 10 + 10 memories
- Antenna: FM swivel telescopic, MW built-in
- Connections: Headphone: 3.5mm, Line-in
- Sound Presets: Voice, Music, Normal
- Controls:
 - Tuning: Up/Down arrows
 - Memo & RDS: P+/P-
 - Volume: Vol+/Vol-
 - Band: 1 tact
 - Power: On/Standby(tact)
- Timer: Alarm/Snooze/Sleep/Clock with RDS
- Audio Power: 800 mW
- DC Power supply: 4 x 1.5V "C" & AC 230V (detached cord)
- Size (WxHxD): 23 x 12.5 x 6cm

Blaupunkt Tech SA - 2011.04

Desktop / Portable AC/DC Digital PLL Radio BTD-7000 (Black) / BTD-7001 (White)

Radio

- Band FM 87.5-108 MHz
MW 522 - 1620 kHz
- RDS Yes (PS/PTY/RT)
- Memories 20+20
- Antenna FM swivel telescopic/ MW built-in

Display

- Type LCD
- Backlight Pale blue (with dimmer)
- Battery low indicator Yes

Timer

- Clock Yes (12h/24h)
- Alarm/Snooze/Sleep Yes/Yes/Yes

Audio

- Speaker 1x 3"
- Power (RMS) 800 mW
- Sound control Presets (Voice/Music/Normal)

Power Supply

- AC built-in 230V (detachable cord)
- DC 4x1.5V "C"

Connections

- Headphones 3.5 mm
- DC in No
- Line in Yes
- Mains yes

Controls

- Power On/Standby (1 tact)
- Tuning ▲ / ▼ / P+ / P- / Memo / RDS (6 tact)
- Volume Vol+ / Vol- (2 tact)
- Band 1 tact
- Timer Alarm/Snooze/Sleep (3 tact)
- Others Audio sound preset (1 tact)

Accessories

- Power cord
 - User Manual
- 22 languages:
German, English, French, Italian, Spanish, Portuguese, Dutch, Swedish, Danish, Finnish, Norwegian, Russian, Greek, Turkish, Polish, Bulgarian, Romanian, Czech, Hungarian, Japanese, Chinese, Arabic.

Size approx.

- WxHxD 23x12.5x6 cm
- Weight 715 g

Subject to any kind of alterations, errors excepted.